

Порядок настройки роутера TL-WR841N:

1. Необходимо подключить роутер к электросети, подключить сетевой провод в WAN порт;
2. Необходимо перевернуть роутер и подключиться к сети используя пароль, который указан в нижней части роутера (либо использовать текущий)



3. Далее необходимо перейти в браузер и в адресную строку набрать сайт tplinklogin.net может быть указан tplinkwifi.net или же для входа в настройки можно использовать 192.168.0.1 или 192.168.1.1 (данная информация указана в нижней части роутера). Авторизовываемся, используя логин и пароль по умолчанию: admin.

4. Выбираем раздел «Quick Setup» -> «Next»

TP-LINK®

Status
Quick Setup
WPS
Network
Wireless
DHCP
Forwarding
Security
Parental Control
Access Control
Advanced Routing
Bandwidth Control
IP & MAC Binding
Dynamic DNS
System Tools

Quick Setup

Run the Quick Setup to manually configure your internet connection and wireless settings.

To continue, please click the **Next** button.

To exit, please click the **Exit** button.

Exit Next

5. Выбираем тип подключения «Dynamic IP» -> «Next»

TP-LINK®

Status
Quick Setup
WPS
Network
Wireless
DHCP
Forwarding
Security
Parental Control
Access Control
Advanced Routing
Bandwidth Control
IP & MAC Binding
Dynamic DNS
System Tools

Quick Setup - WAN Connection Type

Start >> WAN Connection Type >> Wireless >> Finish

The Quick Setup is preparing to set up your connection type of WAN port.

The Router will try to detect the Internet connection type your ISP provides if you select the Auto-Detect option. Otherwise, you need to specify the connection type manually.

- Auto-Detect - Let the Router automatically detect the connection type your ISP provides.
- PPPoE - Usually for ADSL Modem and you will need a PPPoE username and password from your ISP.
- Dynamic IP - Usually for Cable Modem and the router will automatically obtain an IP address from the DHCP server.
- Static IP - This type of connection uses a permanent, fixed (static) IP address that your ISP assigned.

Back Next

6. Выбираем «No, I am connected by another computer (do NOT clone MAC address)» -> «Next»

TP-LINK®

Quick Setup - MAC Clone

Start >> WAN Connection Type >> Wireless >> Finish

Please read help carefully on the right.

Yes, I am connected by the main computer (clone MAC address).

No, I am connected by another computer (do NOT clone MAC address).

WAN MAC Address:

Your PC's MAC Address:

7. Необходимо в поле «Wireless Network Name», задать название сети и перейдя в пункт «Wireless Security», выбрать PSK Password и задать пароль -> «Next».

- Status
- Quick Setup
- WPS
- Network
- Wireless
- DHCP
- Forwarding
- Security
- Parental Control
- Access Control
- Advanced Routing
- Bandwidth Control
- IP & MAC Binding
- Dynamic DNS
- System Tools

Quick Setup - Wireless

Start >> WAN Connection Type >> Wireless >> Finish

Please use the WiFi switch on this device to enable/disable radio

Wireless Radio: Enable

Wireless Network Name: Название (Also called the SSID)

Region: United States

Warning: Ensure you select a correct country to conform local law. Incorrect settings may cause interference.

Mode: 11bgn mixed

Channel Width: Auto

Channel: Auto

Max Tx Rate: 300Mbps

Wireless Security:

Disable Security

WPA-PSK/WPA2-PSK

PSK Password: Пароль

(You can enter ASCII characters between 8 and 63 or Hexadecimal characters between 8 and 64.)

No Change

Back Next

8. Нажимаем кнопку Finish и после перезагрузки устройства (происходит автоматически) подключаемся к ранее созданной сети. На этом, настройка закончена.

- Status
- Quick Setup
- WPS
- Network
- Wireless
- DHCP
- Forwarding
- Security
- Parental Control
- Access Control
- Advanced Routing
- Bandwidth Control
- IP & MAC Binding
- Dynamic DNS
- System Tools

Quick Setup - Finish

Congratulations! This device is now connecting you to the Internet. For detail settings, please click other menus if necessary.

Back Finish